

These power supplies are used for stepper, servo motor drive and high over loaded applications. They will work on both standard 115V and 230V at 50Hz or 60Hz. This toroidal transformer has heavier gauge wires than the normal requirement to avoid the copper loss during the full load output and over load output.

The power supply has a flexible add on option that allows more outputs as needed. Those isolated outputs can be used as logic control or encoder power supply. The main output has 2 large capacitors (10000uF x2) to guarantee the output ripple to minimum.

**AC power connections:**

**115Vac – 2 red wires to neutral & 2 black wires to hot. 220Vac – 1<sup>st</sup> red wire to neutral, 1<sup>st</sup> black wire to 2<sup>nd</sup> red wire, and the 2<sup>nd</sup> black wire to hot.**

Voltage output 1	Output current	Voltage ripple	Output 2	Output 3
54.5 V	0	0	-	-
52.3 V	3.6 A	.20 Vrms	-	-
51.0 V	10.5 A	.74 Vrms	-	-
49.5 V	13.1 A	1.40 Vrms	-	-

Input voltage is 120Vac at 60Hz.